

SAFETY PRECAUTIONS WARNINGS



Risk of fire or electric shock. Basic safety precautions should always be followed when using electrical equipment. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.



Disconnect power to all circuits before wiring fixture.
Install in accordance with all national, state, and local codes.
Do not connect to an ungrounded supply.
Read all fixture markings and labels to ensure correct installation of fixture.



Read all of these installation instructions before installing the track system.
Save these instructions and refer to them when additions to or changes in the track configuration are made.

CAN ICES-005 (A) / NMB-005 (A)

FCC Compliance Statement


This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generated, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

ISED Canada Statement






This class A lighting equipment complies with Innovation, Science and Economic Development (ISED) Canada Standard for radio interference-causing equipment ICES-005, 5th edition.

Déclaration pour ISDE Canada

Ce matériel d'éclairage de classe A est conforme avec la norme sur le matériel brouilleur radio NMB-005, 5ième édition, publié par innovation, science et développement économique (ISDE) Canada.



WIRING DIAGRAM



INSTALLATION STEPS

WARNING: Risk of fire and electrical shock - Fixture to be installed by qualified electrician according to local codes and ordinances.
WARNING: Ensure proper handling of LEDs to limit common problems including: broken connection, loose wiring and damage from electrostatic discharge.

- 1** [A] - Pass cables from fixture through J-box cover plate and J-box mounting plate. Using 2 #8-32 x 1" flat head screws, attach mounting plate to 4" J-box (by others). Make connections Black (+), White (-), Green (neutral). If dimming required: Purple (0-10V +), Gray (0-10V -). Refer to wiring diagram. Using one #8-32 x 1" Button head attach cover plate to mounting plate.
 [B] - With two #8 flat head screws (by others) attach [C] surface mount blocks to a stud (2 per sections). Refer to mounting block guide for [D] block mounting length.
Note: make sure surface mount block is facing the right way up.
 [E] - Align and raise section up to the mounting blocks and secure using 4 set screws on mounting brackets.

ROWS


- 2** [A] - With two #8 flat head screws (by others) attach second [B] surface mount blocks to a stud. Refer to mounting block guide for surface block mounting length.
 [B] - Align corner pins and connect sections with rubber mallet until no gap remains.
 [C] - Secure section using 4 set screws on mounting brackets.
 [D] - Center the electrical connector with the joint between two sections and push all the way in.

CORNERS

- 3** [A] - Align corner pins and connect corner with rubber mallet until no gap remains.
 [B] - Secure section using 2 set screws on mounting brackets.
 [C] - With two #8 flat head screws (by others) attach surface mount blocks to a stud (Should be 2 per sections). Refer to mounting block guide for block mounting length.
 [D] - Align and raise second section up to the mounting blocks. Align to corner pins of the corner and connect with rubber mallet until no gap remains.
 [E] - Secure section using 4 set screws on mounting brackets.
 [F] - Center the electrical connector with the corner and push all the way in.

MAINTENANCE

- 4** **WARNING: Turn off all power to the fixture before any maintenance.**
 [A] - Remove and keep screw from end of J-box.
 [B] - Rotate J-box out of profile to access drivers.



INSTALLATION STEPS

WARNING: Risk of fire and electrical shock - Fixture to be installed by qualified electrician according to local codes and ordinances.
WARNING: Ensure proper handling of LEDs to limit common problems including: broken connection, loose wiring and damage from electrostatic discharge.